#3-84

L.I.S.T. Group

LONG ISLAND
SINCLAIR TIMEX
GROUP

TO:

10 Idle Day Drive
Centerport, N.Y. 11721

Dear Member:

We have a core group now and should schedule a meeting to discuss dues, goals etc. Please call me at the number listed below, and we'll try to arrange a time and place. For openers, lets consider April 1st (Sunday) at 3:00PM, my place.

As for dues, I think $12.00/year will get us started and cover initial costs.

We'll need volunteers to take on the various functions, e.g., maintaining current member lists, mail drop, meeting arrangements, newsletter, so please think about what you'd like to do.

Please send us any ideas, questions or articles you have written, for inclusion in the newsletter. Also, drop us a line on your system configuration.

Very truly yours,

Paul J. Donnelly

W - 212-572-7603
H - 516-261-6934



LONG ISLAND SINCLAIR TIMEX GROUP

NEWSDAY, SUNDAY, MARCH 25, 1984



ORDER TODAY!

O
P1

LEDOUT VERSION 1.2

COPYRIGHT AUG 1983 BY [illegible]

```
   1 REM  AAAAAAAAAAAAAAAAAAAAAAIN.
KEYBOA   COPY   [illegible]  NUT P
RINT X[illegible]
SCUS ?  [illegible]
?RND)E [illegible] RND[illegible] AAAAA
  10 REM   LEDOUT VERSION 1.2
  11 REM       AUG 30 1983
 100 REM  INITIALIZE
 101 POKE 16514,0
 102 POKE 16538,0
 103 POKE 16539,0
 105 POKE 16540,255
 110 LET MENU=1000
 111 REM MENU IS FOR MAIN
          PROGRAM
 121 LET LEDOUT=16542
 123 LET SETUP=16535
 124 GOTO MENU
 125 REM LEDOUT
 127 PRINT ,,"INPUT DECIMAL VALU
E"

 130 INPUT D
 131 PRINT D
 134 REM  NOW CONVERT D TO 3 SEP
ARATE DIGITS
 135 LET H=INT (D/100)
 137 LET T=INT ((D-H*100)/10)
 139 LET U=INT (D-(H*100)-(T*10)

 140 REM NOW CHANGE THAT TO OUR
          SPECIAL CODE
 142 LET H=H-64
 144 LET T=T-32
 146 LET U=U-16
 148 REM COULD HAVE BEEN DONE IN
          125 THRU 129
 150 POKE SETUP,H
 152 POKE SETUP+1,T
 154 POKE SETUP+2 U
 158 REM  CALL LEDOUT
 159 FAST
 160 LET X=USR LEDOUT

 162 SLOW
 165 RETURN
```

DO NOT USE THESE CODES SEE LEDOUT FIG. 2(b)

Fig. 3(a)
LEDOUT

```
 200 REM AD OUT
 203 REM CHOOSE CHANNEL 0
 205 POKE 16514,0
 210 FAST
 215 LET L=USR 10602
 217 REM  X IS SOME SCALING
          FACTOR
 218 LET X=1
 220 LET D=X*PEEK 16515
 225 SLOW
 230 GOSUB 130
 299 GOTO MENU
 300 PRINT "     ";
```

Fig. 3(b)
BASIC LEDOUT
FOR A/D CONVERTER

JUST FOOLING AROUND With 2068



```
10 FOR i=1 TO 10
20 FOR j=1 TO 10
30 FOR k=1 TO 100
40 CIRCLE i,j,k
50 NEXT i: NEXT j: NEXT k
60 STOP
```

What's wrong with this program?

```
   1 REM   AAAAAAAAAAAAAAAAAAAAAA
        THIS IS A WORK AREA
   4 FAST
  10 REM  BASIC LEDOUT
  11 LET H=0
  12 LET T=0
  13 LET U=0
  15 LET OUTPUT=10648
  16 LET BUF=16515
  20 DIM V(4)
 100 REM MAIN
 102 SLOW
 105 PRINT "INPUT DECIMAL VALUE"
 110 INPUT D
 112 PRINT D
 115 LET H=64+INT (D/100)
 120 LET T=32+INT ((D-(H-64)*100
)/10)
 125 LET U=16+INT (D-(H-64)*100-
(T-32)*10)
 130 LET V(1)=H
 135 LET V(2)=T
 140 LET V(3)=U
 145 LET V(4)=0
 150 FOR J=1 TO 50
 155 FOR I=1 TO 3
 160 POKE BUF,V(I)
 162 FAST
 165 LET X=USR OUTPUT
 170 NEXT I
 180 NEXT J
 183 POKE BUF V(4)
 185 LET I=USR OUTPUT
 190 PRINT "AGAIN?"
 192 INPUT A$
 193 IF A$="Y" THEN GOTO 105
 194 IF A$="D" THEN GOTO 200
 195 STOP
 199 REM BLEDOUT
 200 POKE 16514,0
 205 FAST
 210 LET L=USR 10602
 220 LET U=PEEK 16515
 222 SLOW
 225 GOTO 115
 230 STOP
```

Fig. 4
Pure BASIC LEDOUT
(w/ A-to-D)



```
5999 REM A/D TEST
6005 FAST
6010 FOR I=1 TO 10
6020 POKE 16514,0
6030 LET L=USR 10602
6040 LPRINT "VALUE=";PEEK 16515
6050 NEXT I
6060 REM [illegible]
```

TYPICAL VALUE RANGE

```
VALUE=251
VALUE=251
VALUE=241
VALUE=189
VALUE=160
VALUE=42
VALUE=21
VALUE=26
VALUE=2
VALUE=2
```

HARDWARE/REPAIR TIPS

If your ZX/TS keyboard starts acting up, it may be because of poor contact between the keyboard's flat ribbon conductor and the mainframe. I lost the bottom 5 keys on the right hand side recently for no apparent reason. A quick look at the ZX81 schematic shows these keys (B,N,M,.,Break) to be controlled by the A8-A15 line on the 8 connector block. Apparently, the very thin metal film on the plastic carrier can be scraped off during assembly.

Pull the ribbons out of their plugs and hold the ends up to a light. If the metal film was scratched off, you'll see daylight through the traces. Repair is simple, just take a sharp pair of pinking scissors and trim exactly 1/8" from the entire bottom edge of the flat cable (don't forget the notch).

Diagnosing the problem is just as easy - If you loose columns (e.g., V,G,T,5 and 6, Y,H,B) you've lost contact with one of the KBD lines (in this case KBD4) on the 5 pin connector. If rows are lost (as in my case) you'll loose 5 keys, so suspect the eight pin lines.

Sample output from VU-3D



WHAT A CHARACTER

The Game Changer Interface (reviewed elsewhere) enables you to upload ATARI VCS (2600) cartridge contents into your ZX/TS, SAVE them on tape and play them, using the ZX/TS RAM. Since the copy of the game is in RAM, you can also change any part you wish, to suit your own personal style. The ATARI uses a 6507 (processor) so significant changes require programming in 6502 machine code.

However, an understanding of 6502 machine code (MC) is not really necessary for you to change some aspects of your recorded ATARI games. Specifically, any character or icon (a symbol representing you, an object, enemy etc.) can be changed to another shape, just by POKEing new values into its data array.

In order to be represented on the screen, an object must have "bit image" stored somewhere in memory. The game software sends these bits to the hardware which in turn produces the picture you see on the screen. Here's a simple example of a face using an 8 X 8 bit image (that is, 8 bits wide by 8 bits high):



Binary Code	CODE(Hex)
00000000	00
00111110	3E
01101011	6B
00110110	36
00011100	1C
00000000	00
00000000	00
00000000	CD

(a) (b) (c)

Fig. 1

Figure 1(a) gives the binary representation of our "face". Here ones (1's) will represent "turned on" bits and will be dark, while '0's are turned off or blank (the background color will show through). In Fig. 1 c), since this image is exactly 8 bits wide, we're shown the hexadecimal numbers representing one bit bytes. This face can be stored in 8 consecutive memory locations.

If we were to pull up the ATARI game code on the screen a byte at a time and represent it as a series of black and white squares we could "see" the actual character images used in the game. Fig. 2 gives a partial program listing that will do just that.

Before you GOTO 7000 however, you may have to do a little detective work. A typical ATARI cartridge contains a 4K ROM which you will already have downloaded to the 4K of RAM starting at 16514. The 6502 interupts (where the program restarts after something important or bad happens) point to the very high memory locations and addresses pointing to the actual program code will be stored there. You can use the disassembler or monitor to check the top sections of RAM (FFFA through FFFF) for these pointers. You can be reasonably sure the data tables for the characters are not in the immediate areas pointed to by those three sets of 2 bytes and should look elsewhere. Places to look are; 1) boundaries between pages (F000, F300 etc. - a "page" is 256 bits) 2) the beginning of the program 3) addresses which occur frequently.

For ATARI BASIC we used the disassembler to spot check some of these areas and found absolute garbage at the beginning of the program. A good hard look at the 1 REM (see fig 3) also shows the experienced programmer something which just about has to be nonsense. The reoccurance of the same code number several times in succession is very unlikely in an MC program. These clues led us to choose 16514 as a starting address. After offset, this address corresponds to F000(H) in the ATARI.

After GOing to 7000 we obtained the listing in Fig. 4. A pattern of dots is clearly emerging, but hard to identify as letters or figures. Connecting the dots (or using the inverse space instead of an asterisk) can help make the patterns more intelligible. We've done that for the "GOTO" command of ATARI BASIC. You should be able to pick out some other upside-down commands like Print, and Else. The game software and hardware automatically turn these right side up.

How does the routine work? First we dimension some new variables and pick a starting address. These are:

S = Starting address (decimal only)
D(I) = The binary i th Digit of a Byte
A$ = A string which will print either filled-in or MT squares
P = The decimal value of the byte at location S
N = A temporary "part" of the P variable as it is reduced to its D or binary digits.

Next we PEEK the data stored in the currently chosen memory location. The subroutine at 8000 repeatedly divides the decimal number by 2, saving the remainder as D(J) to convert the decimal number to its binary (actually binary still stored as decimal) bit equivalents.

Returning to 7025ff from the subroutine we convert each "character" in the string A$ to its bit pattern: it remains a blank if D(J)≠1 (that is, if its 0) and becomes an asterisk if D(J)= 1.

Finally we print the memory location, decimal value and our new blocked out string of "bits". Don't forget that the actual addresses where this data table reside are some 32000 (decimal) memory locations higher in the ATARI. Also, the conventions used by this programmer may not be used in other games. In ATARI BASIC, in fact, two more, different, techniques are used for addressing the numbers (for MATH) and the display area titles.

You should be able to add these lines to the "change" program with no problems on 4K or less games. You could even just pick an address at random and observe the screen for intelligible patterns. For 8K games create a free standing version of the program addition and try to PEEK the (with the actual cartridge installed) memory locations above 28000. Remember, the bank switching may get in the way.

Some hints at what to change in ATARI BASIC:

1) The symbol table for the display areas (STATUS, PROGRAM etc.) Abbreviating these would free up RAM for your own 6502 MC routines.

2) Change the "Block" graphics character to more interesting picture (e.g., a smiley face).

3) Change the alpha or numeric characters to provide a more interesting display. The letters, for example, can be converted to those of another language.

4) Your own ideas.

```
7000>DIM D(8)
7003 DIM A$(8)
7005 PRINT " INPUT STARTING ADDR
ESS..."
7007 INPUT S
7010 FOR I=S TO S+250
7015 LET P=PEEK I
7020 GOSUB 8000
7025 FOR J=1 TO 8
7030 LET A$(J)=" "
7040 IF D(J)=1 THEN LET A$(J)="*
"
7045 NEXT J
7050 PRINT I;"   ";PEEK I,A$(1 T
O 8)
7060 NEXT I
7900 STOP
8000 FOR J=8 TO 1 STEP (-1)
9010 LET N=INT (P/2)
8020 LET D(J)=INT (P-2*INT (P/2+
.05))
8025 LET P=N
8040 NEXT J
8050 RETURN
9000 STOP
```

Fig. 2

```
    0 REM 5244444267????RNDRND CC
 CONT C INPUT    8((((2>>2?    SLO
W     888CODE :   8Y61444IC SLOW
88 SLOW :      STEP 44 STEP    E S
LOW    SLOW    SLOW  INPUT C INP
UT   INPUT   0?????? CONT   REM
 REM 0 STEP    I444AEN4J SLOW 88
SLOW :      STEP    STEP 4 STEP   L
48CXCC86  INPUT    INPUT E REM    N
444Y44444 CONT CC INPUT     P444Y
444 OR CONT CC INPUT     R **4444
** CONT    CONT I CONT    T **4444
 OR CONT    CONT I CONT    V444Y44
4 ????0?  LEN LEN RETURN LEN LEN
 ?8  UNPLOT LEN LEN UNPLOT LEN L
EN UNPLOT  W?*******?W  SAVE ATN
LEN LEN LEN ATN SAVE  RETURN ***
* SAVE **** RETURN  $8? INPUT CH
R$ CHR$ ? 0*Y???Y LEN LEN LEN RE
TURN LEN LEN LEN  ?XXXXX? ?LEN
     EXP >= SAVE LIST **ATN LEN
```

Fig. 3

* This is Technically termed a "Shape TABLE"!



```
INPUT STARTING ADDRESS...
16514   161
16515   30
16516   32
16517   32
16518   32
16519   32
16520   32
16521   30
16522   162
16523   78
16524   72
16525   78
16526   74
16527   78
16528   64
16529   64
16530   0
16531   168
16532   168
16533   232
16534   168
16535   238
16536   8
16537   0
16538   164
16539   16
16540   16
16541   16
16542   30
16543   18
16544   18
16545   30
16546   165
16547   132
16548   132
16549   132
16550   228
16551   128
16552   4
16553   0
16554   0
16555   164
16556   164
16557   164
16558   196
16559   14
16560   4
16561   0
16562   167
16563   62
16564   34
16568   46
16566   32
16567   32
16568   34
16569   46
16570   168
16571   228
16572   164
16573   164
16574   228
16575   14
16576   4
16577   0
16578   0
16579   224
16580   160
16581   160
16582   224
16583   0
16584   0
16585   0
16586   170
16587   228
16588   132
16589   132
16590   228
16591   132
16592   132
16593   228
16594   0
16595   238
16596   40
16597   238
16598   138
16599   238
```

Fig.4

SPECIAL NOTES

a) TS 2068 owners should already be familiar with the generation of user defined graphics.

b) Use graph paper to lay out your characters.

c) You need not use 8 bytes (in fact our "face" could have been done in 5 bytes, four bytes of data and one attribute "byte"). But, this requires a sound understanding of how the software works.

WHERE TO BUY IT?
(Not Recommendations - just observations)

47th Street Photo		Timex Corp
TS 2068	$99.99	95
TS 2040	55.00	49 - 30 rolls

Software (2000) $15 & up

Commack - Consumers Corner - TS1000

OR Byte, Softsync - Timex Software
Timeworks
ALL TYPES $4.95

New Literature Received:

TUG newsletter - from the Gainesville, Fla. User's Group

Thomas B. Woods PRO/FILE 2068 now available for $29.95 Total Documentation to follow

P.J. Donnelly

GETTING THE LED OUT

In any number of monitoring and/or control uses for your ZX/TS, you may find that using a TV set to check on your system is inconvenient or impractical. This would be so, for example, in outdoor or dirty environments or when you simply wish to check the status of one or two system parameters without the bother of hooking up a TV or monitor. One fairly easy and inexpensive way to do this is to use seven-segment LED (light emitting diode) displays as your system output. Your ZX/TS bus doesn't have enough power in reserve to directly drive these displays, but a few simple IC's and an I/O board can give you this capability.

You must have some sort of 8 bit output port. I used Ener-Z's Report Generator board, but JK Audio's 310 and even Byte Back's BB-1 module (without the relays) should be useable as a buffered output from your computer. The only other hardware you'll need, aside from miscellaneous wire and some resistors, is a 7416, hex inverting buffer; a 4511 BCD (Binary Coded Decimal)-to-7 segment decoder driver; and a 3 character, 7 segment LED display (MAN3). A schematic of this simple circuit is given in Fig 1.

This circuit represents a "middle ground" approach to producing a 3 digit output display. More hardware (latches etc.) could have been used, resulting in permanently lit displays, or we could have used software to create a controlling outer loop to keep the monitoring function as the main operating system. The combination of hardware and software I chose represents a system which uses multiplexing to provide the appearance of a full three digit display.

As you can see from Figure one, we are using the ZX's data lines D_0 through D_3 to send out the Binary coded decimal value of one of three digits (units, tens or hundreds). The correct digit is determined by the data lines D_4 through D_6 which complete the path to ground for the appropriate display. Line D_7 enables and latches the last value from lines D_0 to D_3 into the 4511 which in turn, drives the appropriate elements of the display. Multiplexing is provided by the ML software driver routine shown in Fig 2.

After data is POKEd into the three buffer locations (fig 3-a) the ML program outputs the specially constructed character code for each digit in sequence. This operation occurs so rapidly that the eye is fooled into thinking each digit is lit all the time. If you'd like to see what's really happening, you can either increase the dwell time between digits or use the BASIC listing in Fig 4. The BASIC listing requires no machine code but is, of course, slow.

The software is applicable to the Ener-Z Report Generator board as it stands. However, you can change the address of the call at 16561(d) to the address of your own OUTPUT subroutine. The Report Generator uses a PIO and is I/O mapped. For memory mapped sytems, your OUTPUT subroutine would probably consist of simply putting the value in the accumulator, LOADing the designated memory location with the value, and returning to the driver.

I built this circuit on a small ACE (all circuit evaluator) board and obtained its power from the +5 volt regulator on the R.G. board. The values for the current limiting resistors are not critical, but should be as large as possible to conserve power, while still giving adequate brightness. Don't overlook the 10K pullup resistors for the 7416, or forget to tie the unused inputs to ground.

Fig 3b gives a BASIC driver which I use to obtain a temperature reading from the A/D converter on the R.G. board and output that value to the LED display. The code shown would actually be a subroutine called from a main menu. The display is normally blank. By touching, say, "T" on my keyboard, I would be selecting a menu item which calls the Temperature output routine. All this can be done without the need of a TV screen, if I know in advance (and I do) which key to press. The system could be expanded, with more chips, lots of software and perhaps even LCD displays to actually let you program your computer without a TV. A consideration here would be to use hex buffer drivers instead of BCD.

Note too, that I used "junk box" parts from around my shop to build this particular display. A proper design would use perhaps a 74LS248 for the latch driver (pinout is the same as the 4511). Also remember not to output codes which will turn on all three digits at one time (e.g., code 01111000$_B$ produces all 8's), as current drain will be very high.

LIST GROUP



VU-3D OUTPUT - Shaded

MAG=001.83 ROT 347,259 Z=+00270

LEDOUT



Fig 1 (a)

LEDOUT CODE SENT:

DIGIT	HUNDREDS DIGIT	TENS DIGIT	UNITS DIGIT
0	64	32	16
1	65	33	17
2	66	34	18
3	67	35	19
4	68	36	20
5	69	37	21
6	70	38	11
7	71	39	23
8	72	40	24
9	73	41	25
M	(M+64)	(M+32)	(M+16)

EXAMPLE:

To send the number 888, transmit the following codes in sequence:

24,40,72

i.e.	D_7	D_6	D_5	D_4	D_3	D_2	D_1	D_0
24	0	0	0	1	1	0	0	0
40	0	0	1	0	1	0	0	0
72	0	1	0	0	1	0	0	0

Output will actually be:

72 = 8-- which, when
40 = -8- multiplexed, looks
24 = --8 like 888

Fig 1 (b)

LEDOUT

```
NAME      ADDRESS
          DEC          HEX      MNEMONIC       COMMENTS                    CODE
LEDOUT    16542        4000     LDBC,00FF      Load # of Cycles            01FF00
MAIN      16545        40A1     LDHL,4097                                  219740
          16548        40A4     LDA,4(5)       # of Digits to send         3E04
ENTRY     16550        40A6     PUSH AF        Save A, Flags               F5
          16551                 LDA,(HL)       Get Value to be out-
                                               put from 4097ff             7E
          16552                 LD 4082,A      16514 is poked with
                                               value                       328240
          16555                 POPA           Back to original
                                               digit count                 F1
          16556                 INCHL          Point to next digit         23
          16557                 DECA           Only (A-1)digits left       3D
          16558        40AE     JUMP Z Loop    (40BA)have we done all
                                               4(5) digits?                CABA40
          16561        40B1     CALL OUTPUT    (2998)Send digit out        CD9829
          16564                 CALL DELAY     (40CD)Leave it lit          CDC040
          16567                 JUMP ENTRY     (40A6)Putout next one       C3A640
LOOP      16570        40BA     DEC C          Decrement count             0D
          16571        40BB     RZ             We'll do it FF times
                                               then return to BASIC        C8
          16572        40BC     JUMP MAIN      (40A1)                      C3A140
          16575        40BF     RETURN         Can't get her               C9
DELAY     16576        40C0     LD DE,0040     A simple tim  delay         114000
          16579        40C3     DEC E          For how long we leave       1D
          16580        40C4     JZ 40CA        Each digit on               CACA40
          16583        4067     JUMP 40C3                                  C3C340
          16586        40CA     LDDE,00AA      This is the "outer"         11AA00
          16589        40CD     DEC E          Loop of the                 1D
                       40CE     RZ             Time delay                  C8
                       40CF     JUMP 40CD      Keep looping                C3CD40
                       40D2     RET            can't get here              C9
                                      DATA
NUM       16535        4097     HUNDREDS DIGIT FROM 64 to 73      All  ARE
          16536        4098     TENS           FROM 32 to 41      Special
          16537        4099     UNITS          FROM 17 to 25      BCD
          16538        409A     BLANKING  (255)
          16539,40,411 409B,C,D SPARE
                                 - Fig.2
```

```
ADDRESS:  16534     4096H

16534   26 48 28 18 00 00 FF 00
16542   01 FF 00 21 97 40 3E 05
16550   F5 7E 32 82 40 F1 23 3D
16558   CA BA 40 CD 98 29 CD C0
16566   40 C3 A6 40 0D C8 C3 A1
16574   40 C9 11 40 00 1D CA CA
16582   40 C3 C3 40 11 AA 00 1D
16590   C8 C3 CD 40 C9
```

Hex Dump of Ledout
(Number to be output is 888)